ACTIVE COMBINER - CATV

8 INPUT - 1 OUTPUT



Features

- Zero Phase
- Analog & Digital QAM Inputs
- LF Noise Filter
- 75 Ohm Balanced
- Good Port to Port Isolation

Application

- FM Radio
- Terrestrial Antenna
- CATV DHE
- VHF & UHF Antenna

Specification

Input level : 100 dBuV / Channel (Max)
Band Width : 40 to 1000Mhz
Gain : ± 1dB
Output P1 : 23dBm
Output IP3 : 40dBm
Linearity : ± 1.5dB
Noise Figure : < 2.3 dB
Isolation : >22 dB
No of Input : Eight
No of Output : One
Connector : F Type 75 Ohm

Electrical

Input Voltage : 12VDC
Power Consumption : 3Watt @ 12VDC

Packaging Contents:

Active Combiner - 1No
Adopter - 1No

Mechanical

Type : Indoor
Enclosure : Aluminium
Mounting : 1U Rack Mounting
Top : -10 to 55 Dec C
DC Jack : 2 mm X 5.5mm
Dimension : 490mm X 200mm X 50mm(LBH)
Weight : 2Kg

Ordering Information

Model No : AZCA-08F - 75 Ohm F Female

AMPTRONIX
1st,Floor,No36/32,Sriram Nagar Main Road, Pallipattu, Taramani,
Chennai,Tamil Nadu,INDIA. Postcode: 600113
Mobile: 0 94459 56787
www.amptronix.co.in Email. sales@amptronix.co.in

Notes